


A SERIES UNIVERSAL FLUORESCENT RETROFIT KIT 8 ft. SADDLE BRACKET SOCKET BARS FOR USE WITH 4 T8 LAMPS

Kit # A244-UNV-ALU-BC

Convert an existing 8 ft. two lamp high output T-12 strip or industrial fixture to an 8 ft. fixture with four 4 ft. T8 lamps in tandem.

The conversion kit is designed to fasten to the existing 8 ft. long by 4 in. to 5 in. wide fixture body.

COMPONENTS



SPECIFICATIONS


- 2 x Ballast cover Ballast grade 91% TR Aluminum c/w poly film protection
- 2 x End plates Fixture white finished steel.
- 2 x Center plates Fixture white finished steel.
- 8 x Sockets Bi-pin locking type. (Shunted unless otherwise specified)
- Wiring Color-coded leads #18 TEW solid wire.
- Hardware Self drilling tech screws - 1/4 turn ballast cover fasteners
- Approvals C.S.A. & UL certified.



Individual point of sale packaging available for stocking distributors

KIT TYPE VERIFICATION PROCEDURE

Check critical dimensions of the fixture you're retrofitting by contacting LEI for verification of the correct application.



- Overall width of fixture housing.
- Overall length of fixture housing.

A = 4 in. (102 mm) to 5 in. (127 mm)

B = 96 in. (2440 mm)

Main: (905) 538-7228 Toll free: +1 (855) 264-2200 LED Energy Inc. 174 West Beaver Creek Rd, Richmond Hill, ON. L4B 1B4